arXiv:1301.5655v3 [cs.IT] 12 Feb 2013

A new achievable rate region for multiple access with non casual states

Arun Padakandla and Sandeep Pradhan, *Member, IEEE*

***Abstract*—We derive a new achievable rate region for the problem of communicating over a multiple access channel with states. Our coding technique is based on the ensemble of nested coset codes and the technique of typicality decoding. Exploiting structure in this ensemble, we analyze a more efficient decoding strategy to improve upon the rate region achievable using unstructured random codes. We identify examples for which the achievable rate region based on nested coset codes are strictly larger than the ones achievable using random unstructured codes.**

I. INTRODUCTION

The technique of proving achievability of rate regions in information theory is random coding. Traditionally, the distribution induced on the ensemble of codes is such that individual codewords are mutually independent. Furthermore, in communication models with multiple terminals, the different codebooks are mutually independent of each other. Such an analysis has proved sufficient/optimal for single user and particular multi terminal communication problems.[1]

The problem of distributed reconstruction of modulo-2 sum of binary sources studied by Körner and Marton [1] proved to be the first exception. The authors proposed a coding technique based on nested linear codes that strictly outperforms the best known strategy based on independent unstructured codes. More recently, a similar phenomenon has been identified by Philosof and Zamir [2] for a particular multiple access channel with channel state information distributed at the transmitters (MAC-DSTx). Restricting their attention to a binary doubly dirty MAC-DSTx (BDD-MAC), the authors propose a coding technique, henceforth referred to as PZ-technique, based on nested linear codes that is optimal and moreover, strictly more efficient than the best known strategy based on unstructured independent codes.

Nevertheless ingenious, PZ-technique [2] is particular to the additive nature of the BDD-MAC studied therein. This technique being strictly more efficient than the currently known best strategy based on independent unstructured codes raises the following question. Can the PZ-technique be generalized for communicating over an *arbitrary* discrete MAC-DSTx, and if yes, would this yield an achievable rate region strictly larger than the best known achievable rate region using unstructured independent codes even for non-additive MAC-DSTx?

In this article, we provide affirmative answers to the above questions. We begin by identifying two central elements of PZ-technique 1) decoding mod-2 sum, instead of the pair, of auxiliary codewords and 2) choosing source code of each user's code to be cosets of a common linear code to enable containment of the range of this mod-2 sum of auxiliary codewords. In the first step of our generalization, presented in section III, we propose the use of nested coset codes [3] and analyze decoding the sum of auxiliary codewords over an *arbitrary* MAC-DSTx. The key element in this step is the use of joint typical encoding and decoding that enables us analyze the probability of error over an *arbitrary* MAC-DSTx. Indeed, the analysis of joint typical encoding and decoding of correlated codebooks with statistically dependent codewords involves several new elements. The reader is encouraged to peruse these in proof of theorem 3.

The significance of the rate region proved achievable in the first step is illustrated through examples in section III-C.[2] In particular, we provide examples of MAC-DSTx that are not additive, but yet benefit from decoding the sum of auxiliary codewords chosen from nested coset codes. The channels being non-additive, it is significantly harder to provide analytical upper bounds and we resort to computing rate regions achievable using unstructured independent and nested coset codes. These examples illustrate that structured code based strategies do not hinge on the channel being additive but would benefit as long as the optimizing test channel from the auxiliary inputs to the channel output is not far from additive.

Does the rate region proved achievable using nested coset codes subsume the largest known achievable rate region using unstructured independent codes? It is our belief that strategies based on structured codes are not in lieu of their counterparts based on unstructured codes. In most cases, structured codes enable efficient decoding of a 'compressive'[3] function. The penalty payed in rate for imposing structure in the code is compensated for by the compressive nature of the function. However, for decoding the pair of codewords, structured codes

---

Arun Padakandla and Sandeep Pradhan are with the Department of Electrical and Computer Engineering, University of Michigan, Ann Arbor 48109-2122, USA.

[1] However, characterization of optimal performance in many multi-terminal communication problems such as distributed source coding, interference channel, broadcast channel, multiple description coding remain open.

[2] The coding technique proposed in the first step reduces to that proposed in [2] for BDD-MAC and moreover Philosof and Zamir have proved strict sub-optimality of unstructured independent coding for this BDD-MAC. This in itself establishes significance of theorem 3. Notwithstanding this, it is easy to argue significance of our generalization by appealing to continuity. An additive channel can be perturbed slightly to result in a non-additive channel for which the technique proposed in [2] are not applicable. By continuity of the rate regions as a function of the channel parameters, one can see why a generalization of [2] must perform strictly better than unstructured independent coding. The examples presented in section III-C corroborate this.

[3] $f(U_1, U_2)$ is 'compressive' if $H(f(U_1, U_2))$ is significantly lower than $H(U_1, U_2)$.

are not optimal. Indeed, Körner Marton strategy is outperformed by Berger-Tung strategy for the class of distributions for which the modulo-2 sum is not sufficiently compressive[4]. We therefore take the approach of Ahlswede and Han [4, Section VI], where in structured and unstructured coding techniques are glued together. In section IV, we derive the largest known achievable rate region for communicating over a MAC-DSTx that combines structured and unstructured coding techniques.

If the channel is far from additive, it may not be efficient to decode the sum of auxiliary inputs. For example, if the input, source and output alphabets are a group and MAC-DSTx is doubly dirty with the operation being the group multiplication, then it is natural to decode the product of auxiliary inputs. In other words, the technique of decoding sum of codewords as proposed in [2] must be generalized to decoding any arbitrary bivariate function of the auxiliary inputs. The task of building codes that are closed under other bivariate functions and their analysis using joint typical encoding and decoding rules is quite involved and we only provide pointers in section V and illustrate the gains achievable using group theoretic examples.

Our findings are motivated by a belief that 1) strategies based on independent unstructured codebooks are inadequate and 2) codebooks endowed with algebraic structure may be employed to develop and analyze more efficient coding techniques for multi-terminal communication. Indeed, even after three decades, since the findings of Körner and Marton came to light, we are yet unaware of a coding technique based on independent unstructured codes that achieve rates promised in [1]. On a positive note, recent findings [5], [6], [7] lend sufficient credence for the need of structured codes. Sridharan et. al. [8] propose a coding technique based on lattices for communicating over a $K-$user Gaussian interference channel ($K \geq 3$) that strictly outperforms a natural extension of Han-Kobayashi technique [9]. We propose an analogous coding technique based on nested linear codes [10] for the general discrete $3-$user interference channel and identify an example for which the proposed technique outperforms the natural extension of Han-Kobayashi technique [9]. Krithivasan and Pradhan [11] propose a framework based on structured codes for the problem of distributed source coding that outperforms the best known strategy based on structured codes due to Berger-Tung [12]. We have employed the same ensemble of nested coset codes to strictly enlarge the largest known achievable rate region[5] for the general $3-$user discrete broadcast channel in [13].

We summarize by stating the significance of our contribution. Firstly, we enlarge the largest known achievable rate region for a general discrete MAC-DSTx using nested coset codes. In addition to the BDD-MAC studied by Philosof and Zamir, we present non-additive examples for which the proposed rate region strictly enlarges the currently known largest achievable rate region using unstructured independent codes.[6] Secondly, and perhaps more importantly, our findings hint at a general theory of structured codes. Linear and nested linear codes have been employed to derive communication strategies for particular additive source and channel coding problems that outperform all classical/unstructured known techniques. However the question remains whether these structured code based techniques can be generalized to arbitrary multi-terminal communication problems. Our findings indicate that strategies based on structured codes can be employed to analyze more intelligent encoding and decoding techniques for an arbitrary multi-terminal communication problem. This opens up the possibility of exploiting new degrees of freedom to enlarge achievable rate regions for many multi-terminal communication problems that have resisted a solution. Finally, the analysis of typical set decoding of correlated codebooks with statistically dependent codebooks yields new elements in the proof technique.

II. PRELIMINARIES AND PROBLEM STATEMENT

A. Notation

We employ notation that is now widely adopted in the information theory literature supplemented by the following. We let $\mathcal{F}_q$ denote a finite field of cardinality q. While $+$ denotes addition in $\mathbb{R}$, we let $\oplus$ denote addition in a finite field. The particular finite field, which is uniquely determined (up to an isomorphism) by it's cardinality, is clear from context. When ambiguous, or to enhance clarity, we specify addition in $\mathcal{F}_q$ using $\oplus_q$. For elements a, b, in a finite field, $a \ominus b := a \oplus (-b)$, where $(-b)$ is the additive inverse of b. The $\log$ and $\exp$ functions are taken with respect to the same base. For concreteness, the base may be assumed to be 2, in which case, units for information theoretic quantities such as entropy and mutual information would be bits. If $f : \mathcal{U} \rightarrow \mathcal{X}$ is a map, the n-letter extension of f denoted $f^n : \mathcal{U}^n \rightarrow \mathcal{X}^n$ is defined $f^n(u^n) := (f(u_i) : i = 1, 2, \cdots, n)$.

B. MAC-DSTx

Consider the two user multiple access analogue of the point to point channel with state (PTP-STx) studied by Gelfand and Pinsker [14]. Let $\mathcal{X}_1$ and $\mathcal{X}_2$ denote finite input alphabet sets and $\mathcal{Y}$, the output alphabet set. Transition probabilities depend on a random parameter $\boldsymbol{S} := (S_1, S_2)$, called state, that takes values in a finite set $\mathcal{S} := \mathcal{S}_1 \times \mathcal{S}_2$. The discrete time channel is time invariant, memoryless, used without feedback. Let $W_{Y|\boldsymbol{X}\boldsymbol{S}}(y|\boldsymbol{x}, \boldsymbol{s})$ be probability of observing $y \in \mathcal{Y}$ given $\boldsymbol{x} := (x_1, x_2) \in \mathcal{X} := \mathcal{X}_1 \times \mathcal{X}_2$ is input to the channel in state $\boldsymbol{s} := (s_1, s_2) \in \mathcal{S}$. The state at time i, $\boldsymbol{S_i}$ is (i) independent of $(\boldsymbol{S_t}, \boldsymbol{X_t}, Y_t) : 1 \leq t < i$, and (ii) identically distributed for all i. Let $W_{\boldsymbol{S}}(\boldsymbol{s})$ be probability of MAC-DSTx being in state $\boldsymbol{s} \in \mathcal{S}$. We assume S_j^n is non causally known to encoder j. Input X_j is constrained with respect to an additive cost function

---

[4] If $H(X \oplus Y) > \frac{H(X,Y)}{2}$, then it is better to reconstruct $X \oplus Y$ using the technique of Berger-Tung.

[5] This is obtained by a natural extension of Marton's coding technique proposed for $2-$user broadcast channel. Our findings therefore suggest strict sub-optimality of Marton's coding technique, that has been the largest known for over three decades, for 3 or more users.

[6] This is based on computing the largest known achievable rate region using unstructured independent codes.

$\kappa_j : \mathcal{X}_j \times \mathcal{S}_j \rightarrow [0, \infty)$. We refer to this channel as MAC-DSTx $(\mathcal{S}, W_{\boldsymbol{S}}, \mathcal{X}, \mathcal{Y}, W_{Y|\boldsymbol{X},\boldsymbol{S}}, \kappa)$. The subject of this article is the information theoretic capacity region of MAC-DSTx and in particular, an achievable rate region. We refer the reader to [2] for standard definitions of a code, achievability, capacity. Let $\mathbb{C}(\boldsymbol{\tau}) : = \text{cl}\{\mathbf{R} = (R_1, R_2) \in \mathbb{R}^2 : (\mathbf{R}, \boldsymbol{\tau}) \text{ is achievable}\}$ denote the capacity region when constrained to average cost of $\boldsymbol{\tau} = (\tau_1, \tau_2)$.

C. Largest known achievable rate region

The coding technique that achieves capacity of PTP-STx [14] can be generalized to obtain the largest known inner bound to $\mathcal{C}(\boldsymbol{\tau})$. We provide a characterization of the same below.

Definition 1: Let $\mathbb{D}(\boldsymbol{\tau})$ be collection of distributions $p_{\boldsymbol{U}\boldsymbol{X}\boldsymbol{S}Y}$ on $\mathcal{U}^2 \times \mathcal{X} \times \mathcal{S} \times \mathcal{Y}$, where $\boldsymbol{U}$ denotes U_1, U_2, such that (i) $p_{\boldsymbol{S}} = W_{\boldsymbol{S}}$, (ii) $p_{Y|\boldsymbol{X}\boldsymbol{S}\boldsymbol{U}} = p_{Y|\boldsymbol{X}\boldsymbol{S}} = W_{Y|\boldsymbol{X}\boldsymbol{S}}$, (iii) $p_{U_j|\boldsymbol{S}} = p_{U_j|S_j}$, (iv) $p_{X_j|\boldsymbol{S}\boldsymbol{U}} = p_{X_j|S_jU_j}$ for $j = 1, 2$ (v) $p_{X_j|S_jU_j}(x_j|s_j, u_j) \in \{0, 1\}$ for all $(u_j, s_j, x_j), j = 1, 2$ and (vi) $\mathbb{E}\{\kappa_j(X_j, S_j)\} \leq \tau_j$. For $p_{\boldsymbol{U}\boldsymbol{X}\boldsymbol{S}Y} \in \mathbb{D}(\boldsymbol{\tau})$, let $\alpha(p_{\boldsymbol{U}\boldsymbol{X}\boldsymbol{S}Y})$ be defined as the set

$$\left\{ \begin{array}{l} (R_1, R_2) : R_1 \leq I(U_1; Y, U_2) - I(U_1; S_1), \\ R_2 \leq I(U_2; YU_1) - I(U_2; S_2), \\ R_1 + R_2 \leq I(\boldsymbol{U}; Y) + I(U_1; U_2) - \sum_{j=1}^{2} I(U_j; S_j) \end{array} \right\}$$

and $\alpha(\boldsymbol{\tau})$ be convex closure of $\cup_{p_{\boldsymbol{U}\boldsymbol{X}\boldsymbol{S}Y} \in \mathbb{D}(\boldsymbol{\tau})} \alpha(p_{\boldsymbol{U}\boldsymbol{X}\boldsymbol{S}Y})$.

Theorem 1: $\alpha(\boldsymbol{\tau}) \subseteq \mathcal{C}(\boldsymbol{\tau})$.

Achievability of $\alpha(\boldsymbol{\tau})$ can be proved by employing the encoding technique proposed by Gelfand and Pinsker [14] at each encoder and joint decoding proposed by Ahlswede [15], Liao [16]. In the sequel, we provide an illustration of this coding technique for BDD-MAC.

D. Rate region achievable using unstructured codes for BDD-MAC

Philosof and Zamir prove $\alpha(\boldsymbol{\tau}) \subsetneq \mathbb{C}(\boldsymbol{\tau})$ for BDD-MAC. In order to identify the key elements of PZ-technique, we briefly analyze unstructured coding (this section), PZ-technique (section III-A) and set the stage for a generalization.

BDD-MAC is a MAC-DSTx with binary alphabets $\mathcal{S}_j = \mathcal{X}_j = \mathcal{Y} = \{0, 1\}$, $j = 1, 2$. The state sequences are independent Bernoulli-$\frac{1}{2}$ processes, i.e., $W_{\boldsymbol{S}}(\boldsymbol{s}) = \frac{1}{4}$ for all $\boldsymbol{s} \in \mathcal{S}$. The channel transition is described by the relation $Y = X_1 \oplus_2 S_1 \oplus_2 X_2 \oplus_2 S_2$. An additive Hamming cost is assumed on the input, i.e., $\kappa_j(1, s_j) = 1$ and $\kappa_j(0, s_j) = 0$ for any $s_j \in \mathcal{S}_j$, $j = 1, 2$ and the input is subject to a symmetric cost constraint $\boldsymbol{\tau} = (\tau, \tau)$.

We describe the test channel $p_{\boldsymbol{U}\boldsymbol{S}\boldsymbol{X}Y} \in \mathbb{D}(\boldsymbol{\tau})$ that achieves $\alpha(\boldsymbol{\tau})$. For each user j, consider the test channel that achieves the Gelfand-Pinsker capacity treating the other user as noise i.e., $p_{U_jS_jX_j}(0, 1, 1) = p_{U_jS_jX_k}(1, 0, 1) = \frac{\tau}{2}, p_{U_jS_jX_j}(0, 0, 0) = p_{U_jS_jX_j}(1, 1, 0) = \frac{1-\tau}{2}$. Philosof and Zamir prove $p_{\boldsymbol{U}\boldsymbol{S}\boldsymbol{X}} = p_{U_1S_1X_1}p_{U_2S_2X_2}$ achieves $\alpha(\boldsymbol{\tau}) = \{\mathbf{R} : R_1 + R_2 \leq 2h_b(\tau) - 1\}$.

Let us take a closer look at achievability of the vertex $(2h_b(\tau) - 1, 0)$ using the above test channel. Since user 2 has no message to transmit, it picks a single bin with $2^{nI(U_2;S_2)} = 2^{n(1-h_b(\tau))}$ codewords independently and uniformly from the entire space of binary vectors. User 1 picks 2^{nR_1} bins each with $2^{nI(U_1;S_1)} = 2^{n(1-h_b(\tau))}$ independently and uniformly distributed binary vectors. Encoder 2 observes S_2^n and chooses a codeword, say U_2^n, that is within a Hamming distance of $n\tau$ from S_2^n and transmits $X_2^n = U_2^n \oplus_2 S_2^n$. Encoder 1 performs a similar encoding, except that it restricts the choice of U_1^n to the bin indexed by user 1's message, and transmits $X_1^n = U_1^n \oplus_2 S_1^n$.

What is the maximum rate R_1 at which user 1 can transmit it's message? Decoder receives $Y^n = U_1^n \oplus_2 U_2^n$ and looks for all pairs of codewords that are jointly typical with Y^n. Since any pair of binary $n-$length vectors are jointly typical (U_1 and U_2 are independent and uniform), the decoding rule reduces to finding all pairs of binary $n-$length vectors in the pair of codebooks, that sum to the received vector Y^n. All bins chosen independently without structure imply that any bin of user 1's codebook when added to the user 2's codebook (a single bin) results in $2^{n(2-2h_b(\tau))}$ distinct vectors. Therefore, we cannot hope to pack more than $\frac{2^n}{2^{n(2-2h_b(q))}} = 2^{n(2h_b(q)-1)}$ bins in user 1's codebook.

We make a few observations. Effectively, communication occurs over the $(U_1, U_2) - Y$ channel and the test channel induces the Markov chain $(U_1, U_2) - U_1 \oplus_2 U_2 - Y$. It would therefore be more efficient to communicate information over the $U_1 \oplus_2 U_2 - Y$ channel which suggests an efficient utilization of $U_1 \oplus_2 U_2-$space. Having chosen codewords in each bin independently and moreover the two users' bins independently, each message pair utilizes $2^{n(2-2h_b(\tau))}$ vectors in the $U_1 \oplus_2 U_2-$space. In section III-A, we present PZ-technique, wherein structure in the codebooks is exploited for more efficient utilization of $U_1 \oplus_2 U_2-$space.

We remark that *an explosion in the range of sum of transmitted codewords severely limits achievable rate*. In the next section, we study how codebooks endowed with structure can contain this explosion.

III. AN ACHIEVABLE RATE REGION USING NESTED COSET CODES

A. Nested linear codes for BDD-MAC

We present PZ-technique proposed for BDD-MAC. The encoding and decoding techniques are similar to that stated in II-D except for one key difference. The bins of user 1 and 2's codebooks are cosets of a common linear code. In particular, let λ_I denote a linear code of rate $1 - h_b(\tau)$ that can quantize a uniform source, state S_j^n in our case, within a Hamming distance of $n\tau$. Since user 2 has no message to transmit, it employs λ_I as it's only bin. Encoder 1 employs 2^{nR_1} cosets of λ_I within a larger linear code, called λ_O, as it's bins. Note that rate of λ_O is $R_1 + 1 - h_b(\tau)$. Encoding rule is as described in section II-D.

The codebook of user 2 when added to any bin of user 1's code results in a coset of λ_I, and therefore contains at most $2^{n(1-h_b(\tau))}$ codewords. Moreover, since U_1^n lies in λ_I, user 2's codeword U_2^n and the received vector $Y^n = U_1^n \oplus_2 U_2^n$

lies in the same coset.[7] Since the channel is noiseless user 1 may employ all cosets of λ_I and therefore communicate at rate $h_b(\tau)$ which is larger than $2h_b(\tau) - 1$ for all $\tau \in (0,1)$.

Let us identify key elements of PZ-technique. Each message pair corresponds to at most $2^{n(1-h_b(\tau))}$ vectors in $U_1 \oplus_2 U_2-$space, resulting in a more efficient utilization of this space. This difference is indeed the difference in the sum rate achievable using independent unstructured codes and PZ-technique. We also note the *decoder does not attempt to disambiguate the pair* (U_1^n, U_2^n) *and restricts to decoding* $U_1^n \oplus_2 U_2^n$*. This is motivated by the Markov chain* $(U_1, U_2) - U_1 \oplus_2 U_2 - Y$ *induced by the test channel and the use of structured codebooks that contain the sum.*

It is instructive to investigate the efficacy of this technique if users 1 and 2 employ distinct linear codes $\lambda_{I1}, \lambda_{I2}$ of rate $1 - h_b(\tau)$ instead of a common linear code λ_I. In this case, each message of user 1 can result in $2^{2-2h_b(\tau)}$ received vectors which restricts user 1's rate to $2h_b(q) - 1$ and provides no improvement over the unstructured coding technique. We conclude that *if the source codes of the MAC channel code are nontrivial, as in this case due to the presence of a state, then it maybe beneficial to endow the source code with algebraic structure that contains the range of a bivariate function, and enable the decoder decode this function of chosen codewords.*

Our generalization is based on the above principles. In the first step (section III-B) of our generalization, we decode the sum of chosen codewords over an *arbitrary* MAC using nested coset codes.

B. An achievable rate region for arbitrary MAC-DSTx using nested coset codes

In this section, we present the first step of our generalization - joint typical decoding of sum of auxiliary codewords using nested coset codes over an arbitrary MAC-DSTx.[8] Indeed, the interplay of joint typical encoding and decoding and correlated codebooks result in new elements. The reader is encouraged to peruse details of the proof of theorem 3, in particular that of lemma 2.

We begin with a characterization of test channels followed by achievability.

Definition 2: Let $\mathbb{D}_f(\boldsymbol{\tau}) \subseteq \mathbb{D}(\boldsymbol{\tau})$ be the collection of distributions $p_{\boldsymbol{VSX}Y}$ on $\mathcal{V}^2 \times \mathcal{S} \times \mathcal{X} \times \mathcal{Y}$ where $\mathcal{V}$ is a finite field. For $p_{\boldsymbol{VXS}Y} \in \mathbb{D}_f(\boldsymbol{\tau})$, let $\beta(p_{\boldsymbol{VXS}Y})$ be defined as the set

$$\left\{(R_1, R_2) : R_1 + R_2 \leq \min \left\{ \substack{H(V_1|S_1), \\ H(V_2|S_2)} \right\} - H(V_1 \oplus V_2|Y) \right\}.$$

Let $\beta(\boldsymbol{\tau})$ be defined as the convex closure of the union of $\beta(p_{\boldsymbol{VXS}Y})$ over $p_{\boldsymbol{VXS}Y} \in \mathbb{D}_f(\boldsymbol{\tau})$.

Theorem 2: $\beta(\boldsymbol{\tau}) \subseteq \mathcal{C}(\boldsymbol{\tau})$.

Before we provide a proof, we state the coding technique and indicate achievability of promised rates.

As stated in section III-A, the key aspect is to employ cosets of a common linear as the source code for quantizing the state. We employ three nested linear codes -one each to the two encoders and the decoder- that share a common inner (sparser) code. We begin by describing the encoding rule. The nested linear code provided to encoder j is described through a pair of generator matrices $g_I \in \mathcal{V}^{k \times n}$ and $g_{Oj/I} \in \mathcal{V}^{l_j \times n}$ where (i) g_I and $g_{Oj} :=\begin{bmatrix} g_I \\ g_{Oj/I} \end{bmatrix}$ are generator matrices of inner (sparser) and complete (finer) codes respectively, (ii)

$$\frac{k}{n} \geq 1 - \frac{\min\{H(V_1|S_1), H(V_2|S_2)\}}{\log \pi} \tag{1}$$

$$\frac{k + l_1 + l_2}{n} \leq 1 - \frac{H(V_1 \oplus V_2|Y)}{\log \pi}. \tag{2}$$

with $\pi := |\mathcal{V}|$. Let λ_I and λ_{Oj} denote linear codes corresponding to generator matrices g_I and g_{Oj} respectively. User j's message $M_j^{l_j} \in \mathcal{V}^{l_j}$ indexes the coset $\left(a^k g_I \oplus M_j^{l_j} g_{Oj/I} : a^k \in \mathcal{V}^k\right)$. Encoder j observes state S_j^n and looks for a codeword in the coset indexed by the message that is jointly typical with the state sequence S_j^n according to $p_{S_j V_j}$. If it finds one such codeword, say V_j^n, a vector X_j^n is generated according $\prod_{t=1}^n p_{X_j|S_j V_j}(\cdot|S_{jt} V_{jt})$ and X_j^n is input on the channel. Otherwise, it declares an error. We remark that the encoding rule is identical to the unstructured coding technique except for the source codes being cosets of a linear code.

Now to the decoding rule. The decoder is provided with the nested linear code described through the pair of generator matrices $g_I \in \mathcal{V}^{k \times n}$, $g_{O/I} := \begin{bmatrix} g_{O1/I} \\ g_{O2/I} \end{bmatrix}$, where g_I and $g_{O/I}$ are generator matrices of inner (sparser) and complete (finer) codes respectively. Let λ_O denote the complete code provided to decoder, i.e., the linear code whose generator matrix is $g_O := \begin{bmatrix} g_I \\ g_{O/I} \end{bmatrix}$. Having received Y^n, it lists all codewords in λ_O that are jointly typical with Y^n with respect to $p_{V_1 \oplus V_2, Y}$. If all such codewords belong to a unique coset (of λ_I in λ_O) say $(a^k g_I \oplus m_1^{l_1} g_{O1/I} \oplus m_2^{l_2} g_{O2}/I : a^k \in \mathcal{V}^k)$, it declares $(m_1^{l_1}, m_2^{l_2})$ as the pair of decoded messages. Otherwise, i.e., it finds codewords in different cosets jointly typical with Y^n, it declares an error.

As is typical in information theory, we upper bound the probability of error event by averaging over the ensemble of codes, in this case nested linear codes. For the purpose of proof, we consider three nested coset codes instead of nested linear codes and average uniformly over the entire ensemble of nested coset codes. In particular, we pick entries of each of the constituent generator matrices $g_I, g_{O1/I}, g_{O2/I}$ independently and uniformly from $\mathcal{V}$. Lower bound (1) enable us drive down the probability of encoder not finding a jointly typical codeword in the indexed coset. This bound can be interpreted easily. If we picked codewords according to $\prod_{t=1}^n p_V$, then we need the bin to be of rate $H(V_1) - H(V_1|S_1)$. Since we average uniformly over the ensemble of linear codes, each codeword of a linear code is uniformly distributed over $\mathcal{V}^n$. Hence the bin must of rate at least $\log \pi - H(V_1|S_1)$. The decoder makes an error with arbitrarily small probability if (2) is satisfied. This bound can also be interpreted intuitively. If the codewords were picked according to $p_{V_1 \oplus V_2}$, the upper bound would have been $H(V_1 \oplus V_2) - H(V_1 \oplus V_2|Y)$. In this case, the codewords in the sum of nested linear codes are also uniformly distributed over $\mathcal{V}^n$, and this explains the bound in (2). From (1), (2) it can be verified that $R_1 + R_2 = \frac{l_1+l_2}{n} \leq \min\{H(V_1|S_1), H(V_2|S_2) - H(V_1 \oplus V_2|Y)\}$ is achievable.

---

[7] This is also because the channel is noiseless.

[8] The technique proposed by Philosof and Zamir is particular to the binary doubly dirty MAC - Hamming cost constraint and additive nature of the channel. Moreover, linear codes only achieve the symmetric capacity, and therefore if the output were obtained by passing $(X_1^n \oplus_2 S_1^n, X_2^n \oplus_2 S_2^n)$ through an asymmetric MAC, linear codes though applicable, might not be optimal.

We emphasize that joint typical encoding and decoding enables us decode the sum over an arbitrary MAC-DSTx. Indeed, the analysis of joint typical encoding and decoding with correlated codebooks (users 1 and 2 employ cosets of a the same linear code to partition their channel codes) involves new elements. The informed reader will recognize the need to prove statistical independence of a codeword in a competing sum coset and the pair of cosets indexed by the messages. The dependence built across the codewords and cosets as a consequence of the algebraic structure exemplifies the interplay of algebra and probability. The following proof details these elements.

Proof: We begin with a brief review of coset and nested coset codes. An (n, k) coset is a collection of vectors in $\mathcal{V}^n$ obtained by adding a constant bias vector to a $k-$dimensional subspace of $\mathcal{V}^n$. If $\lambda_O \subseteq \mathcal{V}^n$ and $\lambda_I \subseteq \lambda_O$ are $(n, k + l)$ and (n, k) coset codes respectively, then q^l cosets λ_O/λ_I that partition λ_O is a nested coset code.

A couple of remarks are in order. An (n, k) coset code is specified by a bias vector $b^n \in \mathcal{V}^n$ and a generator matrix $g \in \mathcal{V}^{k \times n}$. If $\lambda_O \subseteq \mathcal{V}^n$ and $\lambda_I \subseteq \lambda_O$ are $(n, k+l)$ and (n, k) coset codes respectively, then there exists a bias vector $b^n \in \mathcal{V}^n$ and a generator matrices $g_I \in \mathcal{V}^{k \times n}$ and $g_O = \begin{bmatrix} g_I \\ g_{O/I} \end{bmatrix} \in \mathcal{V}^{(k+l) \times n}$, such that b^n, g_I specify λ_I and b^n, g_O specify λ_O. Therefore, a nested coset code is specified by a bias vector b^n and any two of the three generator matrices g_I, $g_{O/I}$ and g_O. We refer to this as nested coset code $(n, k, l, g_I, g_{O/I}, b^n)$.

Our coding technique is based on nested coset codes. User j is provided with a nested coset code $(n, k, l_j, g_I, g_{Oj/I}, b_j^n)$ denoted λ_{Oj}/λ_I. User j's message is used to index one among π^{l_j} cosets of λ_{Oj}/λ_I, where $\pi : = |\mathcal{V}|$. For simplicity, we assume message set is $\mathcal{V}^{l_j}$ and $M_j^{l_j} \in \mathcal{V}^{l_j}$ to be uniformly distributed random variable representing user j's message. We let $v_j^n(a^k, m_j^{l_j}) : = a^k g_I \oplus m_j^{l_j} g_{Oj/I} \oplus b_j^n$ denote a generic codeword in λ_{Oj}/λ_I and $c_j(m_j^{l_j}) : = (v_j^n(a^k, m_j^{l_j}) : a^k \in \mathcal{V}^k)$ denote coset corresponding to message $m_j^{l_j}$. We now specify encoding rule. Encoder j observes state sequence S_j^n and declares error if $S_j^n \notin T_{\frac{\delta}{8}}(W_{S_j})$. Else, it looks for codewords $v_j^n(a^k, M_j^{l_j}) \in c_j(M_j^{l_j})$, such that $(S_j, v_j^n(a^k, M_j^{l_j})) \in T_{\frac{\delta}{4}}(p_{S_j V_j})$. If it finds at least one such codeword, one of them, say $v_j^n(a^k, M_j^{l_j})$, is chosen uniformly at random and $e_j(M_j^{l_j}, S_j^n) : = f_j^n(v_j^n(a^k, M_j^{l_j}), S_j^n)$ is input to the channel, where $f : \mathcal{V} \times \mathcal{S}_j \rightarrow \mathcal{X}_j$ is a map such that $p_{X_j|S_j V_j}(f(s_j, v_j)|s_j, v_j) = 1$. Otherwise, an error is declared.

We now specify the decoding rule. The decoder is provided with nested coset code $(n, k, l, g_I, g_{O/I}, b^n)$ denoted λ_O/λ_I where $l = l_1 + l_2$, $g_{O/I} : = \begin{bmatrix} g_{O1/I} \\ g_{O2/I} \end{bmatrix}$ and $b^n : = b_1^n \oplus b_2^n$. With a slight abuse of notation, we let $\boldsymbol{m^l} : = (m_1^{l_1}, m_2^{l_2}) \in \mathcal{V}^{\boldsymbol{l}} : = \mathcal{V}^{l_1} \times \mathcal{V}^{l_2}$ represent a pair of messages and analogously $\boldsymbol{M^l} : = (M_1^{l_1}, M_2^{l_2})$ denote random variables corresponding to the users messages. For $a^k \in \mathcal{V}^k$ and $\boldsymbol{m^l} \in \mathcal{V}^l$, let $v^n(a^k, \boldsymbol{m^l}) : = a^k g_I \oplus \boldsymbol{m^l} g_{O/I} \oplus b^n$ and $c(\boldsymbol{m^l}) : = (v^n(a^k, \boldsymbol{m^l}) : a^k \in \mathcal{V}^k)$ denote a generic codeword in coset corresponding to message pair $\boldsymbol{m^l}$ and coset corresponding to message pair $\boldsymbol{m^l}$ respectively. The decoder receives Y^n and declares error if $Y^n \notin T_{\frac{\delta}{2}}(p_Y)$. Else, it lists all codewords $v^n(a^k, \boldsymbol{m^l}) \in \lambda_O$ such that $(v^n(a^k, \boldsymbol{m^l}), Y^n) \in T_\delta^n(p_{V_1 \oplus V_2, Y})$. If it finds all such codewords in a unique coset say $c(\hat{\boldsymbol{m}}^{\boldsymbol{l}})$ of λ_O/λ_I, then it declares $\hat{\boldsymbol{m}}^{\boldsymbol{l}}$ as the pair of decoded messages. Otherwise, it declares an error.

As is typical in information theory, we derive an upper bound on probability of error by averaging the error probability over the ensemble of nested coset codes. We average over the ensemble of nested coset codes by letting the bias vectors $B_j^n : j = 1, 2$ and generator matrices $G_I, G_{Oj/I} : j = 1, 2$ mutually independent and uniformly distributed over their respective range spaces. Let $\Lambda_{Oj}/\Lambda_I : j = 1, 2$ and Λ_O/Λ_I denote the random nested coset codes $(n, k, l_j, G_I, G_{Oj/I}, B_j^n) : j = 1, 2$ and $(n, k, l, G_I, G_{O/I}, B^n)$ respectively. For $a^k \in \mathcal{V}^k$, $\boldsymbol{m^l} \in \mathcal{V}^{\boldsymbol{l}}$, let $V_j^n(a^k, m_j^{l_j}) : j = 1, 2$, $V^n(a^k, \boldsymbol{m^l})$ denote corresponding random codewords in $\Lambda_{Oj}/\Lambda_I : j = 1, 2$ and Λ_O/Λ_I respectively. Let $C_j(m_j^{l_j}) : = (V_j^n(a^k, m_j^{l_j}) : a^k \in \mathcal{V}^k)$ and $C(\boldsymbol{m^l}) : = (V^n(a^k, \boldsymbol{m^l}) : a^k \in \mathcal{V}^k)$ denote random cosets in $\Lambda_{Oj}/\Lambda_I : j = 1, 2$ and Λ_O/Λ_I corresponding to message $m_j^{l_j} : j = 1, 2$ and $\boldsymbol{m^l}$ respectively. We now analyze error events and upper bound probability of error.

We begin by characterizing error events at encoder. If $\epsilon_{j1} : = \{S_j^n \notin T_{\frac{\delta}{8}}(W_{S_j})\}$,

$$\phi(s_j^n, m_j^{l_j}) : = \sum_{a^k \in \mathcal{V}_j^k} 1_{\left\{\left(V_j^n(a^k, m_j^{l_j}), s_j^n\right) \in T_{\frac{\delta}{4}}^n(p_{V_j S_j})\right\}}$$

and $\epsilon_{j2} : = \{\phi(S_j^n, M_j^{l_j}) = 0\}$, then $\epsilon_{j1} \cup \epsilon_{j2}$ is the error event at encoder j. By frequency typicality, $P(\epsilon_{j1}) \leq \frac{\zeta}{8}$ for sufficiently large n. An upper bound on $P(\epsilon_{j2} \cap \epsilon_{j1}^c)$ can be derived by following the arguments in [3]. Findings in [3] imply existence of $N_{j2} \in \mathbb{N}$ such that $\forall n \geq N_{j2}$, $P(\epsilon_{2j} \cap \epsilon_{j1}^c) \leq \frac{\zeta}{8}$ if $\frac{k}{n} > 1 - \frac{H(V_j|S_j)}{\log \pi}$.

The error event at the decoder is $\epsilon_3 \cup \epsilon_4$, where $\epsilon_3 : = \{Y^n \notin T_{\frac{\delta}{2}}^n(p_Y)\}$ and

$$\epsilon_4 : = \bigcup_{\hat{\boldsymbol{m}}^{\boldsymbol{l}} \neq \boldsymbol{M^l}} \bigcup_{a^k \in \mathcal{V}^k} \left\{\left(V^n(a^k, \hat{\boldsymbol{m}}^{\boldsymbol{l}}), Y^n\right) \in T_\delta^n(p_{V_1 \oplus V_2, Y})\right\}.$$

By conditional frequency typicality, there exists $N_3 \in \mathbb{N}$ such that $\forall n \geq N_3$, $P((\cup_{j=1}^2 \epsilon_{j1} \cup \epsilon_{j2})^c \cap \epsilon_3) \leq \frac{\zeta}{8}$. It remains to



Fig. 1. Bounds on sum rate for example 1

upper bound $P(((\cup_{j=1}^{2}\epsilon_{j1}\cup\epsilon_{j2})\cup\epsilon_3)^c\cap\epsilon_4)$. In appendix A, we prove that if $\frac{k+l}{n}<1-\frac{H(V_1+V_2|Y)}{\log\pi}$, there exists $N_4\in\mathbb{N}$ such that $\forall n\geq N_4$, $P(\epsilon_4)\leq\frac{\zeta}{8}$. ■

C. Examples

We now illustrate significance of theorem 3 through the following non-additive examples. A few remarks are in order. The examples needing to be non-additive lends it considerably hard to provide analytical upper bounds for the rate region achievable using unstructured codes.[9] We therefore resort to computation. Computation of $\alpha(\boldsymbol{\tau})$ involves two auxiliary alphabets of cardinality at least 3 each just for the binary MAC-DSTx. Sampling the probability matrix with any reasonable step size is infeasible. It is our conjecture that the additional letter in the auxiliary alphabet enables convexification of the rate region.[10]. The sum rate bound for the unstructured coding technique projected below is therefore obtained through computation involving binary auxiliary alphabet sets followed by convexification (timesharing between different cost). Secondly, one will expect the gains projected in [2] to carry over for channels close to additive. The following examples confirm that. It is therefore reasonable to believe that restriction of the size of the auxiliary alphabet is not altering the results. The following examples being non-additive lends PZ-technique inapplicable. For the following examples, we assume alphabet sets to be binary $\mathcal{S}_j=\mathcal{X}_j=\{0,1\}$, $j=1,2$, (ii) uniform and independent states, i.e., $W_{\boldsymbol{S}}(\boldsymbol{s})=\frac{1}{4}$ for all $\boldsymbol{s}\in\mathcal{S}$, (iii) a Hamming cost function $\kappa_j(1,s_j)=1$ and $\kappa_j(0,s_j)=0$ for any $s_j\in\mathcal{S}_j$, $j=1,2$. We resort to computing upper bound achievable using unstructured codes and sum rate achievable using nested coset codes. These are plotted in figures 1-4.

Example 1: The channel transition matrix is given in table I. 1) An upper bound on sum rate achievable using unstructured codes and 2) sum rate achievable using structured are plotted in figure 1.

$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$	$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$
0000	0.93	1000	0.08
0001	0.04	1001	0.84
0010	0.06	1010	0.86
0011	0.89	1011	0.11
0100	0.11	1100	0.87
0101	0.81	1101	0.08
0110	0.79	1110	0.09
0111	0.12	1111	0.91

TABLE I
CHANNEL TRANSITION MATRIX EXAMPLE 1



Fig. 2. Bounds on sum rate for example 2

Example 2: The channel transition matrix is given in table II. 1) An upper bound on sum rate achievable using unstructured codes and 2) sum rate achievable using structured are plotted in figure 2.

Example 3: The channel transition matrix is given in table III. 1) An upper bound on sum rate achievable using unstructured codes and 2) sum rate achievable using structured are plotted in figure 3.

Example 4: The channel transition matrix is given in table

$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$	$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$
0000	0.90	1000	0.03
0001	0.04	1001	0.89
0010	0.06	1010	0.89
0011	0.83	1011	0.06
0100	0.08	1100	0.95
0101	0.83	1101	0.03
0110	0.89	1110	0.05
0111	0.10	1111	0.94

TABLE II
CHANNEL TRANSITION MATRIX EXAMPLE 2

$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$	$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$
0000	0.92	1000	0.07
0001	0.08	1001	0.92
0010	0.06	1010	0.96
0011	0.94	1011	0.10
0100	0.10	1100	0.88
0101	0.92	1101	0.08
0110	0.95	1110	0.11
0111	0.06	1111	0.91

TABLE III
CHANNEL TRANSITION MATRIX EXAMPLE 3

---

[9] We recognize that the analytical upper bound derived in [2] is a key element of the findings therein.

[10] The optimal test channel for the binary doubly dirty MAC does not contradict this.



Fig. 3. Bounds on sum rate for example 3



Fig. 4. Bounds on sum rate for example 4

IV. 1) An upper bound on sum rate achievable using unstructured codes and 2) sum rate achievable using structured are plotted in figure 4.

In computing above bounds, we restricted (i) auxiliary alphabet sets $\mathcal{U}_1, \mathcal{U}_2$ to be of cardinality at most 2, (ii) X_j to be a function of U_j, S_j.[11] The resulting space of probability distributions that respect the cost constraints was sampled with a step size of 0.015 in each dimension. The resulting bound on the sum rate achievable using unstructured codes (without time sharing) is marked with blue crosses (denoted α in the legend) in the plots. More formally, for a cost constraint $\boldsymbol{\tau} = (\tau, \tau)$, α is representative of

$$\sup_{p_{\boldsymbol{USX}Y} \in \overline{\mathbb{D}}(\boldsymbol{\tau})} I(\boldsymbol{U};Y) + I(U_1;U_2) - \sum_{j=1}^{2} I(U_j;S_j)$$

where $\overline{\mathbb{D}}(\boldsymbol{\tau}) \subseteq \mathbb{D}(\tau)$ is the collection of distributions defined on $\mathcal{U}^2 \times \mathcal{S} \times \mathcal{X} \times \mathcal{Y}$ where (i) $|\mathcal{U}| \leq 2$ and the channel transition probability matrix is as provided in the corresponding table. The resulting upper bound is obtained as an upper convex envelope. Similarly, sum rate achievable using nested coset codes is marked with red circles (denoted β in the legend) in the plots. More formally, for a cost constraint $\boldsymbol{\tau} = (\tau, \tau)$, β is representative of

$$\sup_{p_{\boldsymbol{USX}Y} \in \overline{\mathbb{D}}_f(\boldsymbol{\tau})} \min\left\{H(U_1|S_1), H(U_2|S_2) - H(U_1 \oplus U_2|Y)\right\}$$

where $\overline{\mathbb{D}}_f(\boldsymbol{\tau}) \subseteq \mathbb{D}(\tau)$ is the collection of distributions defined on $\mathcal{U}^2 \times \mathcal{S} \times \mathcal{X} \times \mathcal{Y}$ where (i) $|\mathcal{U}| \leq 2$ and the channel transition probability matrix is as provided in the corresponding table.

$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$	$S_2X_2S_1X_1$	$W_{Y\|\boldsymbol{SX}}(0\|\cdot)$
0000	0.93	1000	0.08
0001	0.04	1001	0.84
0010	0.06	1010	0.86
0011	0.89	1011	0.11
0100	0.11	1100	0.87
0101	0.81	1101	0.08
0110	0.79	1110	0.09
0111	0.12	1111	0.91

TABLE IV
CHANNEL TRANSITION MATRIX EXAMPLE 4

We conclude with remarks on the choice of examples. The channels studied in the examples are obtained by slightly perturbing an additive channel and are therefore ‘close to being additive’. The reader may question this choice. Since theorem 3 characterizes the rate region achievable by decoding the sum of auxiliary codewords, we do not expect this to outperform the technique of decoding the pair of codewords unless the effective channel induced between the auxiliary inputs (U_1, U_2) and output Y is not far from being additive. As mentioned earlier, techniques based on structured codes are more efficient only if the function decoded is compressive enough to offset the loss incurred for imposing structure in the codebooks. For the problem in context, the sum rate achievable using structured codes is $H(U_1|S_1)+H(U_2|S_2)-H(U_1U_2|Y)$, and therefore, we expect gains if $H(U_1 \oplus U_2|Y)$ is sufficiently smaller when compared to $H(U_1U_2|Y)$.

Does this imply the applicability of structured codes only to problems that are close to being additive. The findings of theorem 3 are only hinting at potential gains achievable by decoding *bivariate functions* through the simplest example of field addition. Indeed, a comprehensive technique will involve choosing the appropriate bivariate function for the problem in context and building codes whose source codes are closed with respect to that bivariate function. We elaborate on this in section V. For the case of field addition, the example provided by Philosof and Zamir [2] is indeed canonical and the examples provided herein, provided for the sake of completeness, only corroborates the phenomenon at play.

We conclude by stating that the rate region achievable using nested coset codes for the above examples can be potentially enhanced by incorporating unstructured code techniques. In other words, we build on [4], to propose a universal strategy that subsumes both unstructured and structured coding techniques. This provides further credence for potential enlargement of achievable rate regions using structured codes.

---

[11] Since the objective function $I(\boldsymbol{U};Y)+I(U_1;U_2)-\sum_{j=1}^{2} I(U_j;S_j)$ is (i) convex in $p_{X_1|U_1S_1}$ for a fixed $P_{U_1|S_1}, p_{U_2|S_2}, p_{X_2|U_2S_2}$, (ii) convex in $p_{X_2|U_2S_2}$ for a fixed $P_{U_1|S_1}, p_{U_2|S_2}, p_{X_1|U_1S_1}$ this restriction is valid.

IV. A UNIFIED ACHIEVABLE RATE REGION

In this section, we put together the techniques of unstructured and structured random coding to derive the largest known achievable rate region for a general MAC-DSTx. Our approach is similar to that proposed by Ahlswede and Han [4, Section VI] for the problem of reconstructing mod-2 sum of distributed binary sources. We begin with a characterization of valid test channels.

Definition 3: Let $\mathbb{D}_{sf}(\boldsymbol{\tau}) \subseteq \mathbb{D}(\boldsymbol{\tau})$ be the collection of distributions $p_{\boldsymbol{UVSX}Y}$ on $(\mathcal{U} \times \mathcal{V})^2 \times \mathcal{S} \times \mathcal{X} \times \mathcal{Y}$ where $\mathcal{U}$ is a finite set and $\mathcal{V}$ is a finite field. For $p_{\boldsymbol{UVSX}Y} \in \mathbb{D}_{sf}(\boldsymbol{\tau})$, let $\mathcal{R}(p_{\boldsymbol{UVXS}Y})$ be defined as

$$\left\{\begin{array}{l}(R_1,R_2): 0 \leq R_1 \leq I(U_1;U_2Y) - I(U_1;S_1)\\ +\min\{H(V_j|U_j,S_j): j=1,2\} - H(V_1 \oplus V_2|U_1,U_2,Y)\\ 0 \leq R_2 \leq I(U_2;U_1Y) - I(U_2;S_2)\\ +\min\{H(V_j|U_j,S_j): j=1,2\} - H(V_1 \oplus V_2|U_1,U_2,Y)\\ R_1+R_2 \leq I(U_1U_2;Y) + I(U_1;U_2) - \sum_{j=1}^{2} I(U_j;S_j)\\ +\min\{H(V_j|U_j,S_j): j=1,2\} - H(V_1 \oplus V_2|U_1,U_2,Y)\end{array}\right\},$$

where $\oplus$ is addition in $\mathcal{V}$. Let $\mathcal{R}(\boldsymbol{\tau})$ be defined as the convex closure of the union of $\mathcal{R}(p_{\boldsymbol{UVXS}Y})$ over the collection $p_{\boldsymbol{UVXS}Y} \in \mathbb{D}_{sf}(\boldsymbol{\tau})$ of valid test channels.

Theorem 3: $\mathcal{R}(\boldsymbol{\tau}) \subseteq \mathcal{C}(\boldsymbol{\tau})$.

In the interest of brevity, we briefly state the coding technique. Each user builds an unstructured code over $\mathcal{U}$ and a nested linear code over $\mathcal{V}$ The nested linear codes share a common inner (sparser) code. The unstructured code is partitioned into bins (Gelfand-Pinsker binning). Each user's message is split into two parts - one indexing a bin in the unstructured code and one indexing a coset in the nested linear code. Encoder j picks a pair of codewords, say (U_j^n, V_j^n) jointly typical with the observed state sequence from the indexed pair of bins and transmits an input vector generated according to $p_{X_j|V_jU_jS_j}$. Having received Y^n, decoder looks for all triples $(U_1^n, U_2^n, V_1^n \oplus V_2^n)$ of codewords in the corresponding codebooks that is jointly typical with Y^n according to $p_{\boldsymbol{U},V_1 \oplus V_2,Y}$ and declares the quadruple of bin indices as the decoded message. Achievability is proved by upper bounding the probability of error averaged over the ensemble of codes.

Remark 1: $\alpha(\boldsymbol{\tau}) \subseteq \mathcal{R}(\boldsymbol{\tau})$ and moreover $\mathcal{R}(\boldsymbol{\tau})$ is the largest known achievable rate region for the general MAC-DSTx.

V. ENLARGING ACHIEVABLE RATE REGION USING CODES OVER GROUPS

Consider a quaternary doubly dirty MAC-DSTx (QDD-MAC), with $\mathcal{S}_j = \mathcal{X}_j = \mathcal{Y} = \{0,1,2,3\}$, $j = 1,2$. The state sequences are independent and uniformly distributed, i.e., $W_{\boldsymbol{S}}(\boldsymbol{s}) = \frac{1}{16}$ for all $\boldsymbol{s} \in \mathcal{S}$. The channel transition is described by the relation $Y = X_1 \diamondplus S_1 \diamondplus X_2 \diamondplus S_2$, where $\diamondplus$ denotes addition mod-4. All nonzero symbols have equal cost, i.e., $\kappa_j(x,s_j) = 1$ for all $x \in \{1,2,3\}$ and $\kappa_j(0,s_j) = 0$ for all $s_j \in \mathcal{S}_j$, $j = 1,2$ and the input is subject to a symmetric cost constraint $\boldsymbol{\tau} = (\tau,\tau)$.



Fig. 5. Sum rate achievable using unstructured, nested coset and group codes for test channel (3)

What would be the achievable rate region for QDD-MAC using unstructured codes? The technique proposed in [2] that yields an upper bound on the sum rate achievable using unstructured code for BDD-MAC cannot be employed to derive an analogous upper bound for QDD-MAC.[12] We are led to conjecture the form of the optimizing test channel takes the form

$$p_{X_jU_j|S_j}(x_j, x_j \diamondplus s_j|s_j) = \begin{cases} \frac{\tau}{3} & \text{for } x_j = 0 \\ 1-\tau & \text{otherwise.} \end{cases} \tag{3}$$

The conjecture is based on empirical evidence obtained for the corresponding quaternary dirty point to point Gelfand-Pinsker channel. The sum rate achievable using the above test channel is the upper convex envelope of the function $\alpha : [0,\frac{3}{4}] \rightarrow [0,\infty)$ defined as $\alpha(\tau) = \max\left\{-2\tau\log(\frac{\tau}{3}) - 2(1-\tau)\log(1-\tau)) - 2, 0\right\}$. Since 4 is a prime power, there exists a unique field $\mathcal{F}_4$ of cardinality 4. Do nested coset codes built over $\mathcal{F}_4$ achieve a larger sum rate?

We are unable to characterize sum rate achievable using nested coset codes and the dimensionality of the space of probability distributions lends computation infeasible. We conjecture the above test channel optimizes the sum rate achievable using nested coset codes. In any case computing the sum rate achievable using nested coset codes for the above test channel is instructive. It can be verified that the sum rate achievable using the above test channel with nested coset codes is the upper convex envelope of the function $\beta : [0,\frac{3}{4}] \rightarrow [0,\infty)$ defined as $\beta(\tau) = \max\left\{-\tau\log(\frac{\tau}{3}) - (1-\tau)\log(1-\tau)) - \frac{1}{2}, 0\right\}$.

The sum rate achievable for the above test channel using unstructured and nested coset codes is plotted in figure 5. It is no surprise that nested coset codes perform poorly. The channel operation is *not* the field addition $\oplus_4$ in $\mathcal{F}_4$. Instead, $\diamondplus$ is the group addition in the Abelian group $\mathbb{Z}_4$. This suggests we build codes over groups that are closed under group operation and decode the sum $\diamondplus$ of auxiliary inputs.

Linear codes are kernels of field homomorphisms that are also known as linear transformations. This lends them the property of closure under field addition. We build *group codes* that are kernels of group homomorphisms. Group codes are closed under group operation. We choose a group code Γ_I.

---

[12] In fact, this technique cannot be generalized to an arbitrary finite field. For this case, Wyner's technique [17, Section II] seems more promising.

Cosets of Γ_I in a larger group code Γ_{Oj}, that contains Γ_I, is chosen to be user j's code. Cosets of Γ_I form bins of each user's codebook. The encoding is similar to that with nested coset codes. The decoder decodes group addition $\oplus$ of auxiliary codewords.

What are the rates achievable using group codes? In the interest of brevity, we only provide a sampling of results for QDD-MAC. We refer the interested reader to [18] for a study of group codes and their potential in multi-terminal communication systems. Just as linearity forced us to enlarge rate of a bin from $I(U_j;S_j)$ to $\log|\mathcal{U}_j| - H(U_j|S_j)$, closure under group operation will entail an analogous rate loss. The algebraic structure being more degenerate, the rate loss is in general larger. Yet, for the QDD-MAC, the sum rate achievable using group codes for the test channel in 3 is larger. In particular, the sum rate achievable using group codes is the upper convex envelope of the function $\beta : [0, \frac{3}{4}] \rightarrow [0, \infty)$ defined as $\beta(\tau) = \max\left\{\min\left\{-\tau\log(\frac{\tau}{3}) - (1-\tau)\log(1-\tau), 2h_b(\frac{2\tau}{3})\right\}, 0\right\}$. In figure 5, the sum rate achievable using group codes for the above test channel is plotted.

The results in this section, though incomplete, point to a rich theory of strategies for multi-terminal communication systems based on structured code ensembles. Gains crucially rely on the compressive nature of the bivariate function and the ability to build efficient codes with rich algebraic structure. It is therefore no surprise that all of earlier findings were based on exploiting modulo-2 sum - the simplest compressive function with binary arguments - using linear codes - an ensemble that has been studied at length from different perspectives.

APPENDIX A
AN UPPER BOUND ON $P(\epsilon_4)$

In this appendix, we derive an upper bound on $P(\epsilon_4)$. As is typical in proofs of channel coding theorems, this step involves establishing statistical independence of cosets $C_j(M_j^{l_j}) : j = 1, 2$ corresponding to the message pair and any codeword $V^n(\hat{a}^k, \hat{m}^l)$ in a competing sum coset. We establish this in lemma 2. We begin with the necessary spadework. Throughout this appendix, we employ the notation introduced in proof of theorem 3.

Lemma 1: If $\boldsymbol{m^l} \neq \boldsymbol{\hat{m}^l}$, then for any triple $\nu_1^n, \nu_2^n, \hat{\nu}^n \in \mathcal{V}^n$,

$$P\begin{pmatrix} V_j^n(0^k, m_j^{l_j}) = \nu_j^n : j=1,2, \\ V^n(0^k, \boldsymbol{\hat{m}^l}) = \hat{\nu}^n \end{pmatrix} = P\begin{pmatrix} V_j^n(0^k, m_j^{l_j}) \\ = \nu_j^n : j=1,2 \end{pmatrix} P\begin{pmatrix} V^n(0^k, \boldsymbol{\hat{m}^l}) \\ = \hat{\nu}^n \end{pmatrix}$$

Proof: By definition of $V_j(0^k, m_j^{l_j}) : j = 1, 2$ and $V(0^k, \boldsymbol{m^l})$,

$$\begin{aligned} & P\begin{pmatrix} V_j^n(0^k, m_j^{l_j}) = \nu_j^n : j=1,2, \\ V^n(0^k, \boldsymbol{\hat{m}^l}) = \hat{\nu}^n \end{pmatrix} \\ = \; & P\begin{pmatrix} \begin{bmatrix} m_1^{l_1} & 0^{l_2} \end{bmatrix} G_{O/I} \oplus B_1^n = \nu_1^n, \begin{bmatrix} 0^{l_1} & m_2^{l_2} \end{bmatrix} G_{O/I} \oplus B_2^n = \nu_2^n \\ \begin{bmatrix} \hat{m}_1^{l_1} & \hat{m}_2^{l_2} \end{bmatrix} G_{O/I} \oplus B_1^n \oplus B_2^n = \hat{\nu}^n \end{pmatrix} \\ = \; & P\begin{pmatrix} \begin{bmatrix} m_1^{l_1} & 0^{l_2} \end{bmatrix} G_{O/I} \oplus B_1^n = \nu_1^n, \begin{bmatrix} 0^{l_1} & m_2^{l_2} \end{bmatrix} G_{O/I} \oplus B_2^n = \nu_2^n \\ \begin{bmatrix} \tilde{m}_1^{l_1} & \tilde{m}_2^{l_2} \end{bmatrix} G_{O/I} = \hat{\nu}^n \end{pmatrix} \end{aligned} \quad (4)$$

where $\tilde{m}_j^{l_j} = \hat{m}_j^{l_j} \ominus m_j^{l_j}$. We now prove, using a counting argument, the term on right hand side of (4) is $\frac{1}{\pi^{3n}}$[13]. Since $\hat{m}^l \neq m^l$, there exists $t \in [l]$ such that $\hat{m}_t \neq m_t$. Given any $(l-1)$ vectors $g_{O/I,j} \in \mathcal{V}^n : j \in \{1, \cdots, l\} \setminus \{t\}$, there exists a unique triple of vectors $(g_{O/I,t}, b_1^n, b_2^n) \in \mathcal{V}^n \times \mathcal{V}^n \times \mathcal{V}^n$ such that $\begin{bmatrix} m_1^{l_1} & 0^{l_2} \end{bmatrix} g_{O/I} \oplus b_1^n = \nu_1^n$, $\begin{bmatrix} 0^{l_1} & m_2^{l_2} \end{bmatrix} g_{O/I} \oplus b_2^n = \nu_2^n$ and $\begin{bmatrix} \tilde{m}_1^{l_1} & \tilde{m}_2^{l_2} \end{bmatrix} g_{O/I} = \hat{\nu}^n$.[14] Hence

$$\left|\left\{ \begin{matrix} (g_{O/I}, b_1^n, b_2^n) \in \\ \mathcal{V}^{l \times n} \times \mathcal{V}^n \times \mathcal{V}^n \end{matrix} : \begin{matrix} \begin{bmatrix} m_1^{l_1} & 0^{l_2} \end{bmatrix} g_{O/I} \oplus B_1^n = \nu_1, \\ \begin{bmatrix} 0^{l_1} & m_2^{l_2} \end{bmatrix} g_{O/I} \oplus B_2^n = \nu_2 \\ \begin{bmatrix} \tilde{m}_1^{l_1} & \tilde{m}_2^{l_2} \end{bmatrix} g_{O/I} = \hat{\nu}^n \end{matrix} \right\}\right| = \pi^{(l-3)n}.$$

The mutual independence and uniform distribution of $G_{O/I}, B_1, B_2^n$ implies the term on RHS of (4) is indeed $\frac{1}{\pi^{3n}}$. It remains to prove

$$P(V_j^n(0^k, m_j^{l_j}) = \nu_j^n : j = 1, 2) P(V^n(0^k, \boldsymbol{\hat{m}^l}) = \hat{\nu}^n) = \frac{1}{\pi^{3n}}.$$

Note that codewords of a uniform random linear code are uniformly distributed i.e., $P\left(V^n(0^k, \boldsymbol{\hat{m}^l}) = \hat{\nu}^n\right) = \frac{1}{\pi^n}$. Using the definition of $V^n(0^k, \boldsymbol{\hat{m}^l})$, we only need to prove

$$P\begin{pmatrix} \begin{bmatrix} m_1^{l_1} & 0^{l_2} \end{bmatrix} G_{O/I} \oplus B_1^n = \nu_1, \\ \begin{bmatrix} 0^{l_1} & m_2^{l_2} \end{bmatrix} G_{O/I} \oplus B_2^n = \nu_2 \end{pmatrix} = \frac{1}{\pi^{2n}}.$$

This follows again from a counting argument. For every matrix $g_{O/I} \in \mathcal{V}^{l \times n}$, there exists a unique pair of vectors $b_1^n, b_2^n \in \mathcal{V}^n$ such that $\begin{bmatrix} m_1^{l_1} & 0^{l_2} \end{bmatrix} G_{O/I} \oplus B_1^n = \nu_1^n$, and $\begin{bmatrix} 0^{l_1} & m_2^{l_2} \end{bmatrix} G_{O/I} \oplus B_2^n = \nu_2^n$ thus yielding

$$\left|\left\{ \begin{matrix} (g_{O/I}, b_1^n, b_2^n) \in \\ \mathcal{V}^{l \times n} \times \mathcal{V}^n \times \mathcal{V}^n \end{matrix} : \begin{matrix} \begin{bmatrix} m_1^{l_1} & 0^{l_2} \end{bmatrix} G_{O/I} \oplus B_1^n = \nu_1^n, \\ \begin{bmatrix} 0^{l_1} & m_2^{l_2} \end{bmatrix} G_{O/I} \oplus B_2^n = \nu_2^n \end{matrix} \right\}\right| = \pi^{(l-2)n}, \quad (5)$$

and the proof is completed using the mutual independence and uniform distribution of $G_{O/I}, B_1^n, B_2^n$. ■

Lemma 2: For any $\boldsymbol{\hat{m}^l} \neq \boldsymbol{m^l}$, and any $\hat{a}^k \in \mathcal{V}^k$, the pair of cosets $C_j(m_j^{l_j}) : j = 1, 2$ is statistically independent of $V^n(\hat{a}^k, \boldsymbol{\hat{m}^l})$.

Proof: For $j = 1, 2$, let $\nu_j^n(a_j^k) \in \mathcal{V}^n$ for each $a_j^k \in \mathcal{V}^k$, and $\hat{\nu}^n \in \mathcal{V}^n$. We need to prove

$$\begin{aligned} P(C_j^n(m_j^{l_j}) = (\nu_j(a_j^k) : a_j^k \in \mathcal{V}^k) : j = 1, 2, \\ V^n(\hat{a}^k, \boldsymbol{\hat{m}^l}) = \hat{\nu}^n) \\ = P(C_j^n(m_j^{l_j}) = (\nu_j(a_j^k) : a_j^k \in \mathcal{V}^k) : j = 1, 2) \\ P(V^n(\hat{a}^k, \boldsymbol{\hat{m}^l}) = \hat{\nu}^n) \end{aligned}$$

for every choice of $\nu_j(a_j^k) \in \mathcal{V}^n : a_j^k \in \mathcal{V}^k, j = 1, 2$ and $\hat{\nu}^n \in \mathcal{V}^n$.

If (i) for $j = 1$ or $j = 2$, $(\nu_j(a_j^k \oplus \tilde{a}_j^k) \ominus \nu_j(0^k)) \neq (\nu_j(a_j^k) \ominus \nu_j(0^k)) \oplus (\nu_j(\tilde{a}_j^k) \ominus \nu_j(0^k))$ for any pair a_j^k, $\tilde{a_j}^k \in \mathcal{V}^k$, or (ii) $\nu_1(a_1^k) \ominus v_1(0^k) \neq \nu_2(a_1^k) \ominus v_2(0^k)$ for some $a_1^k \in \mathcal{V}^k$, then LHS and first term of RHS are zero and equality holds. Otherwise,

---

[13] Recall $\pi := |\mathcal{V}|$.

[14] row j of $g_{O/I}$ is $g_{O/I,j}$

$$
\begin{aligned}
&P\left(C_j^n(m_j^{l_j})=(\nu_j(a_j^k):a_j^k\in\mathcal{V}^k):j=1,2,V^n(\hat{a}^k,\hat{\boldsymbol{m}}^{\boldsymbol{l}})=\hat{\nu}^n\right)\\
&=P\begin{pmatrix} a_2^kG_I=\nu_2(a^k)\ominus\nu_2(0^k):a_2^k\in\mathcal{V}^k,\\ V_j^n(0^k,m_j^{l_j})=\nu_j(0^k):j=1,2,\\ V^n(0^k,\hat{\boldsymbol{m}}^{\boldsymbol{l}})=\hat{\nu}^n\ominus(\nu_2(\hat{a}^k)\ominus\nu_2(0^k))\end{pmatrix} && (6)\\
&=P\begin{pmatrix} a_2^kG_I=\nu_2(a^k)\ominus\\ \nu_2(0^k):a_2^k\in\mathcal{V}^k\end{pmatrix}P\begin{pmatrix} V_j^n(0^k,m_j^{l_j})=\nu_j(0^k):j=1,2,\\ V^n(0^k,\hat{\boldsymbol{m}}^{\boldsymbol{l}})=\hat{\nu}^n\ominus(\nu_2(\hat{a}^k)\ominus\nu_2(0^k))\end{pmatrix} && (7)\\
&=P\begin{pmatrix} a_2^kG_I=\nu_2(a^k)\ominus\\ \nu_2(0^k):a_2^k\in\mathcal{V}^k\end{pmatrix}P\begin{pmatrix}\left[m_1^{l_1}\;\;0^{l_2}\right]G_{O/I}\oplus B_1^n=\nu_1(0^k),\\ \left[0^{l_1}\;\;m_2^{l_2}\right]G_{O/I}\oplus B_2^n=\nu_2(0^k)\end{pmatrix}\\
&\qquad\qquad P\left(V^n(\hat{a}^k,\hat{\boldsymbol{m}}^{\boldsymbol{l}})=\hat{\nu}^n\right) && (8)\\
&=P\begin{pmatrix} a_2^kG_{I_2}=\nu_2(a^k)\ominus\nu_2(0^k):a_2^k\in\mathcal{V}^k\\ \left[m_1^{l_1}\;\;0^{l_2}\right]G_{O/I}\oplus B_1^n=\nu_1(0^k),\\ \left[0^{l_1}\;\;m_2^{l_2}\right]G_{O/I}\oplus B_2^n=\nu_2(0^k)\end{pmatrix}P\begin{pmatrix}V^n(\hat{a}^k,\hat{\boldsymbol{m}}^{\boldsymbol{l}})\\ =\hat{\nu}^n\end{pmatrix} && (9)\\
&=P\left(C_j^n(m_j^{l_j})=(\nu_j(a_j^k):a_j^k\in\mathcal{V}^k):j=1,2\right)P\begin{pmatrix}V^n(\hat{a}^k,\hat{\boldsymbol{m}}^{\boldsymbol{l}})\\ =\hat{\nu}^n\end{pmatrix} && (10)
\end{aligned}
$$

where i) (8) and (10) follow from definition of cosets $C_j(m_j^{l_j})$, (ii) (7) and (9) follow from independence of G_{I_2} and the collection $(G_{O/I}, B_1^n, B_2^n)$ and (iii) (6) follows from lemma 1. ■

We emphasize consequence of lemma 2 in the following remark.

Remark 2: If $m^l \neq \hat{m}^l$, then conditioned on event $\left\{M^l = m^l\right\}$, received vector Y^n is statistically independent of $V^n(\hat{a}^k, \hat{m}^l)$ for any $\hat{a}^k \in \mathcal{V}^k$. We establish truth of this statement in the sequel. Let $\mathcal{C}_j$ denote the set of all ordered π^k-tuples of vectors in $\mathcal{V}^n$. Observe that

$$
\begin{aligned}
&P\begin{pmatrix}M^l=m^l,Y^n=y^n,\\ V^n(\hat{a}^k,\hat{m}^l)=\hat{\nu}^n\end{pmatrix}=\sum_{C_1\in\mathcal{C}_1}\sum_{C_2\in\mathcal{C}_2}\sum_{\boldsymbol{s}^n\in\mathcal{S}^n}P\begin{pmatrix}M^l=m^l,S^n=s^n\\ C_1(m_1^{l_1})=C_1\\ C_2(m_2^{l_2})=C_2\\ V^n(\hat{a}^k,\hat{m}^l)=\hat{v}^n,\\ Y^n=y^n\end{pmatrix}\\
&=\sum_{C_1\in\mathcal{C}_1}\sum_{C_2\in\mathcal{C}_2}\sum_{\boldsymbol{s}^n\in\mathcal{S}^n}P\begin{pmatrix}M^l=m^l\\ S^n=s^n\end{pmatrix}P\begin{pmatrix}C_1(m_1^{l_1})=C_1\\ C_2(m_2^{l_2})=C_2\end{pmatrix}\\
&\qquad P\left(V^n(\hat{a}^k,\hat{m}^l)=\hat{v}^n\right)P\left(Y^n=y^n\middle|\substack{C_j(m_j^{l_j})=C_j:j=1,2\\ S^n=s^n,M^l=m^l}\right) && (11)\\
&=\sum_{C_1\in\mathcal{C}_1}\sum_{C_2\in\mathcal{C}_2}\sum_{\boldsymbol{s}^n\in\mathcal{S}^n}P\begin{pmatrix}M^l=m^l,Y^n=y^n,S^n=s^n\\ C_j(m_j^{l_j})=C_j:j=1,2\end{pmatrix}P\begin{pmatrix}V^n(\hat{a}^k,\hat{m}^l)\\ =\hat{v}^n\end{pmatrix}\\
&=P\left(M^l=m^l,Y^n=y^n\right)P\left(V^n(\hat{a}^k,\hat{m}^l)=\hat{\nu}^n\right)
\end{aligned}
$$

where (11) follows from (i) independence of random objects that characterize codebook and (S^n, M^l), (ii) lemma 2 and (iii) statistical independence of the inputs $X_j(M_j^{l_j}, S_j^n) : j = 1, 2$ to the channel and the codeword $V^n(\hat{a}^k, \hat{m}^l)$ conditioned on the specific realization of cosets $(C_j(M_j^{l_j}) : j = 1, 2)$ and the event $\left\{M^l = m^l\right\}$. Moreover, since $P(V^n(\hat{a}^k, \hat{m}^l) = \hat{\nu}^n) = \frac{1}{\pi^n}$, we have $P\left(M^l = m^l, Y^n = y^n, V^n(\hat{a}^k, \hat{m}^l) = \hat{\nu}^n\right) = \frac{1}{\pi^n}P(M^l = m^l, Y^n = y^n)$.

We are now equipped to derive an upper bound on $P(\epsilon_4)$. Observe that

$$
\begin{aligned}
P(\epsilon_4)&\leq P\left(\bigcup_{\hat{a}^k\in\mathcal{V}^k}\bigcup_{\substack{m^l,\hat{m}^l\\ m^l\neq\hat{m}^l}}\left\{\substack{(V^n(\hat{a}^k,\hat{m}^l),Y^n)\in T_\delta(p_{V_1\oplus V_2,Y})\\ M^l=m^l}\right\}\right)\\
&\leq\sum_{\hat{a}^k\in\mathcal{V}^k}\sum_{\substack{m^l,\hat{m}^l\\ m^l\neq\hat{m}^l}}\sum_{\substack{y^n\\ \in T_\delta(Y)}}\sum_{\substack{v^n\in\\ T_{2\delta}(V_1\oplus V_2|y^n)}}P\begin{pmatrix}V^n(a^k,\hat{m}^l)=v^n\\ M^l=m^l,Y^n=y^n\end{pmatrix}\\
&\leq\sum_{\hat{a}^k\in\mathcal{V}^k}\sum_{\substack{m^l,\hat{m}^l\\ m^l\neq\hat{m}^l}}\sum_{\substack{y^n\in\\ T_\delta(Y)}}\sum_{\substack{v^n\in\\ T_{2\delta}(V_1\oplus V_2|y^n)}}P\begin{pmatrix}V^n(a^k,\hat{m}^l)\\ =v^n\end{pmatrix}P\begin{pmatrix}M^l=m^l\\ Y^n=y^n\end{pmatrix}\\
&\leq\sum_{\hat{a}^k\in\mathcal{V}^k}\sum_{\hat{m}^l\in\mathcal{V}^l}\sum_{\substack{y^n\\ \in T_\delta(Y)}}\sum_{\substack{v^n\in\\ T_{2\delta}(V_1\oplus V_2|y^n)}}\frac{P(Y^n=y^n)}{\pi^n}\\
&\leq\sum_{\substack{y^n\\ \in T_\delta(Y)}}\frac{\pi^{k+l}|T_{2\delta}(V_1\oplus V_2|y^n)|}{\pi^n}\\
&\leq\exp\left\{-n\log\pi\left(1-\frac{H(V_1\oplus V_2|Y)+3\delta}{\log\pi}-\frac{k+l}{n}\right)\right\}. && (12)
\end{aligned}
$$

where (12) follows from the uniform bound of $\exp\left\{n\left(H(V_1 \oplus V_2|Y) + 3\delta\right)\right\}$ on $|T_{2\delta}(V_1 \oplus V_2|y^n)|$ for any $y^n \in T_\delta(Y)$, for sufficiently large n (bound on conditional frequency typical set). (12) is the desired upper bound on $P(\epsilon_5)$.

ACKNOWLEDGMENT

This work was supported by NSF grant CCF-0915619 and CCF-1116021.

The first author thanks (i) Raj Tejas Suryaprakash for lending his expertise with regard to computing and plotting results for examples 1-4, (ii) Aria Sahebi for useful discussions with respect to material presented in section V, and (iii) Deepanshu Vasal for general discussions.

REFERENCES

[1] J. Körner and K. Marton, "How to encode the modulo-two sum of binary sources (corresp.)," IEEE Trans. Inform. Theory, vol. 25, no. 2, pp. 219 – 221, Mar 1979.

[2] T. Philosof and R. Zamir, "On the loss of single-letter characterization: The dirty multiple access channel," IEEE Trans. Inform. Theory, vol. 55, pp. 2442–2454, June 2009.

[3] A. Padakandla and S. Pradhan, "Nested linear codes achieve marton's inner bound for general broadcast channels," in 2011 IEEE ISIT Proceedings, 31 2011-aug. 5 2011, pp. 1554 –1558.

[4] R. Ahlswede and T. Han, "On source coding with side information via a multiple-access channel and related problems in multi-user information theory," IEEE Trans. on Info. Th., vol. 29, no. 3, pp. 396 – 412, may 1983.

[5] G. Bresler, A. Parekh, and D. Tse, "The approximate capacity of the many-to-one and one-to-many gaussian interference channels," Information Theory, IEEE Transactions on, vol. 56, no. 9, pp. 4566 –4592, sept. 2010.

[6] B. Nazer and M. Gastpar, "Computation over multiple-access channels," IEEE Trans. on Info. Th., vol. 53, no. 10, pp. 3498 –3516, oct. 2007.

[7] D. Krithivasan and S. Pradhan, "Lattices for distributed source coding: Jointly gaussian sources and reconstruction of a linear function," Information Theory, IEEE Transactions on, vol. 55, no. 12, pp. 5628 –5651, dec. 2009.

[8] S. Sridharan, A. Jafarian, S. Vishwanath, S. Jafar, and S. Shamai, "A layered lattice coding scheme for a class of three user gaussian interference channels," in 2008 46th Annual Allerton Conference Proceedings on, sept. 2008, pp. 531 –538.

[9] T. Han and K. Kobayashi, "A new achievable rate region for the interference channel," Information Theory, IEEE Transactions on, vol. 27, no. 1, pp. 49 – 60, jan 1981.

[10] A. Padakandla, A. Sahebi, and S. Pradhan, "A new achievable rate region for the 3-user discrete memoryless interference channel," in 2012 IEEE ISIT Proceedings, july 2012, pp. 2256 –2260.

[11] D. Krithivasan and S. Pradhan, "Distributed source coding using abelian group codes: A new achievable rate-distortion region," IEEE Trans. Inform. Theory, vol. 57, no. 3, pp. 1495 –1519, march 2011.

[12] T. Berger, Multiterminal Source Coding. In: The Information Theory Approach to Communications (ed. G. Longo), CISM Courses and Lecture Notes No. 229. Springer, Wien-New York, 1977.

[13] A. Padakandla and S. Pradhan, "A new coding theorem for three user discrete memoryless broadcast channel," available at `http://arxiv.org/abs/1207.3146`.

[14] S. I. Gel'fand and M. S. Pinsker, "Coding for channel with random parameters," Problems of Ctrl. and Info. Th., vol. 19, no. 1, pp. 19–31, 1980.

[15] R. Ahlswede, "Multi-way communication channels," in Proceedings of 2nd ISIT, Thakadsor, Armenian SSR, Sept 1971, pp. 23–52.

[16] H. Liao, "A coding theorem for multiple access communications," in Proceedings of 2nd ISIT, Thakadsor, Armenian SSR, 1972.

[17] A. D. Wyner and J. Ziv, "The rate-distortion function for source coding with side information at the decoder," IEEE Trans. Inform. Theory, vol. 22, no. 1, pp. 1–10, January 1976.

[18] A. Sahebi and S. Pradhan, "On distributed source coding using Abelian group codes," in Proceeindgs of 2012 50th Annual Allerton Conference on Communication, Control, and Computing (Allerton), oct. 2012.